



iWASH & iVAC DATE & TIME SETTING

1. Press **shift + menu/ok** together to access the **run screen**
2. Press **menu/ok** to access the main menu
3. Use the **up** or **down arrow** to scroll to **Change D/H**, once selected it will flash
4. Press **menu/ok** to access settings
5. Use the **right arrow** to scroll to the setting that needs to be adjusted
6. Once the setting you want to adjust is flashing use the **up** or **down arrow** to change the value.
7. Once all the settings are adjusted as required press **menu/ok** to save settings
8. To exit the main menu press the **left arrow**

SETTING THE iWASH & iVAC OPERATING TIME

DO NOT adjust this if 24 Hrs 7 days a week operation is required as this is a default setting

1. Press **shift + menu/ok** together to access the **run screen**
2. Press **menu/ok** to access the main menu
3. Use the **up** or **down arrow** to scroll to **Parameters**, once selected it will flash
4. Press **menu/ok** to access settings, the screen will display **CC1 Counter**
5. Use the **up arrow** to scroll to **H1**
6. Use the **right arrow** to scroll through the options
7. The **right arrow** will take you to a flashing **A**. Using the **up** or **down arrow** you can scroll thru **A, B, C** and **D**. This allows you to have 4 different operating times. Please note: The B, C & D operating times should only be used if you have different operating times for different days of the week.
8. Starting with **A**, and once its flashing use the **right arrow** to scroll to the next setting. From here you can select what days of the week you would like this program to run.
9. Use the **up** or **down arrow** to select the corresponding number to the day, use the **right arrow** to scroll to the next day.
 - 0 = Monday
 - 1 = Tuesday
 - 2 = Wednesday
 - 3 = Thursday
 - 4 = Friday
 - 5 = Saturday
 - 6 = Sunday

NB: If you want to exclude a particular day for this operating time leave it as “-“.
10. After selecting the days for this specific operating time press the **right arrow**. The **On Time hour** will begin to flash. Use the **up** or **down arrow** to select the appropriate hour. Use the **right arrow** to scroll to the **On Time Minutes**. Use the **up** or **down arrow** to select the appropriate minutes
11. Continue scrolling with the **right arrow** to program the **Off Time** hours and minutes in the same way as detailed in Step 10
12. Once all the fields have been completed press **menu/ok**. The screen will ask you to confirm the settings, press **menu/ok** while **yes** is flashing to confirm, you will return to the H1 screen and the new operating times will be flashing
13. Press **menu/ok** to return to the **coin counter** screen